



# **GPT-12000 Specifications**

The specifications apply when the GPT-12000 is powered on for at least 30 minutes under +15°C~+35°C

## **GPT-12004 (Front)**



## GPT-12003/12002/12001 (Front)



## **GPT-12004 (Rear)**



## GPT-12003/12002/12001 (Rear)



# (All models are available with optional GPIB or LAN)

Model \ Func.	AC Withstanding	DC Withstanding	Insulation Resistance	Ground Bond	Ground Continuity
GPT-12001	٧				٧
GPT-12002	٧	٧			٧
GPT-12003	٧	٧	٧		٧
GPT-12004	٧	٧	٧	٧	٧

AC WITHSTANDING	
Output-Voltage Range	0.050kV~5.000kV
Output-Voltage Resolution	1V
Output-Voltage Accuracy	± (1% of setting + 5V) [no load]
Maximum Rated Load	200 VA (5kV/40mA)
Maximum Rated Current	40mA (0.5kV< V $\leq$ 5kV)
	10mA ( $0.05$ kV $\leq$ V $\leq$ 0.5kV)
Output-Voltage Waveform	Sine wave
Output-Voltage Frequency	50 Hz / 60 Hz selectable
Voltage Regulation	$\pm$ (1% + 5V) [maximum rated load $\rightarrow$ no load]
Voltmeter Accuracy	$\pm$ (1% of reading + 5V)
Current Measurement Range	1μA~40.00mA
Current Best Resolution	1μΑ / 10μΑ
Current Measurement Accuracy	$\pm$ (1.5% of reading + 30 $\mu$ A)
Current Offset	60μA Maximum
Window Comparator Method	Yes
ARC Detect	Yes
RAMP UP (Rise Time)	0.1s~999.9s

T (886) 2 2268-0389 F (886)2 2268-0639 www.gwinstek.com

RAMP DOWN (Fall Time)	0.000000.00		
` '	0.0s~999.9s		
TIMER (Test Time)	OFF, 0.3s~999.9s		
TIMER Accuracy	±(100ppm + 20ms) 0.0s~999.9s		
WAIT TIME			
GND	ON/OFF		
DC WITHSTANDING	0.00014/20.000147		
Output-Voltage Range	0.050kV~6.000kV 1V		
Output-Voltage Resolution			
Output-Voltage Accuracy	± (1% of setting + 5V) [no load]		
Maximum Rated Load	50W (5kV/10mA)		
Maximum Rated Current	$10\text{mA } (0.5\text{kV} < \text{V} \leq 6\text{kV})$		
	$2mA (0.05kV \le V \le 0.5kV)$		
Voltage Regulation	$\pm$ (1% + 5V) [maximum rated load $\rightarrow$ no load]		
Voltmeter Accuracy	± (1% of reading + 5V)		
Current Measurement Range	1μA~10.00mA		
Current Best Resolution	0.1μΑ /1μΑ /10μΑ		
Current Measurement Accuracy	$\pm$ (1.5% of reading + 3 $\mu$ A) when I Reading < 1mA		
	$\pm$ (1.5% of reading + 30 $\mu$ A) when I Reading $\ge$ 1mA		
Current Offset	5μA Maximum		
Window Comparator Method	Yes		
ARC Detect	Yes		
RAMP UP (Rise Time)	0.1s~999.9s		
RAMP DOWN (Fall Time)	0.0s~999.9s		
TIMER (Test Time)	OFF, 0.3s~999.9s		
TIMER Accuracy	±(100ppm + 20ms)		
WAIT TIME	0.0s~999.9s		
GND	ON/OFF		
INSULATION RESISTANCE			
Output Voltage	50V~1200V dc		
Output-Voltage Resolution	50V		
Output-Voltage Accuracy	± (1% of setting + 5V) [no load]		
Resistance Display			
Test Voltage	Display Range		
50V≦V≦100V	0.1ΜΩ~ 10.00GΩ		
150V≦V≦450V	0.1ΜΩ~ 20.00GΩ		
500V≦V≦1200V	0.1ΜΩ~ 50.00GΩ		
	0.11012 50.00012		
Resistance Measurement	U.1Wit2 50.00Gt2		
	Measurement Range / Accuracy		
Resistance Measurement			
Resistance Measurement Test Voltage	Measurement Range / Accuracy		
Resistance Measurement Test Voltage	Measurement Range / Accuracy $0.1M\Omega^{\sim}1M\Omega$ : ±(5% of reading + 3 count)		
Resistance Measurement Test Voltage	Measurement Range / Accuracy $0.1M\Omega^{\sim}1M\Omega : \pm (5\% \text{ of reading + 3 count})$ $1.1M\Omega^{\sim}50M\Omega : \pm (5\% \text{ of reading + 1 count})$		
Resistance Measurement Test Voltage 50V≦V≦450V	Measurement Range / Accuracy $0.1M\Omega^{\sim}1M\Omega$ : $\pm(5\%$ of reading + 3 count) $1.1M\Omega^{\sim}50M\Omega$ : $\pm(5\%$ of reading + 1 count) $50.1M\Omega^{\sim}2G\Omega$ : $\pm(10\%$ of reading + 1 count)		
Resistance Measurement Test Voltage 50V≦V≦450V	Measurement Range / Accuracy $0.1M\Omega^{\sim}1M\Omega : \pm (5\% \text{ of reading } + 3 \text{ count})$ $1.1M\Omega^{\sim}50M\Omega : \pm (5\% \text{ of reading } + 1 \text{ count})$ $50.1M\Omega^{\sim}2G\Omega : \pm (10\% \text{ of reading } + 1 \text{ count})$ $0.1M\Omega^{\sim}1M\Omega : \pm (5\% \text{ of reading } + 3 \text{ count})$ $1.1M\Omega^{\sim}500M\Omega : \pm (5\% \text{ of reading } + 1 \text{ count})$		
Resistance Measurement Test Voltage 50V≦V≦450V	Measurement Range / Accuracy $0.1M\Omega^{\sim}1M\Omega : \pm (5\% \text{ of reading} + 3 \text{ count})$ $1.1M\Omega^{\sim}50M\Omega : \pm (5\% \text{ of reading} + 1 \text{ count})$ $50.1M\Omega^{\sim}2G\Omega : \pm (10\% \text{ of reading} + 1 \text{ count})$ $0.1M\Omega^{\sim}1M\Omega : \pm (5\% \text{ of reading} + 3 \text{ count})$ $1.1M\Omega^{\sim}500M\Omega : \pm (5\% \text{ of reading} + 1 \text{ count})$ $500.1M\Omega^{\sim}9.999G\Omega : \pm (10\% \text{ of reading} + 1 \text{ count})$		
Resistance Measurement Test Voltage 50V ≤ V ≤ 450V  500V ≤ V ≤ 1200V	Measurement Range / Accuracy $0.1M\Omega^{\sim}1M\Omega : \pm (5\% \text{ of reading} + 3 \text{ count})$ $1.1M\Omega^{\sim}50M\Omega : \pm (5\% \text{ of reading} + 1 \text{ count})$ $50.1M\Omega^{\sim}2G\Omega : \pm (10\% \text{ of reading} + 1 \text{ count})$ $0.1M\Omega^{\sim}1M\Omega : \pm (5\% \text{ of reading} + 3 \text{ count})$ $1.1M\Omega^{\sim}500M\Omega : \pm (5\% \text{ of reading} + 1 \text{ count})$ $500.1M\Omega^{\sim}9.999G\Omega : \pm (10\% \text{ of reading} + 1 \text{ count})$ $10G\Omega^{\sim}50G\Omega : \pm (20\% \text{ of reading} + 1 \text{ count})^*$		
Resistance Measurement Test Voltage 50V ≦ V ≦ 450V  500V ≦ V ≦ 1200V  Voltage Regulation	Measurement Range / Accuracy $0.1M\Omega^{\sim}1M\Omega : \pm (5\% \text{ of reading} + 3 \text{ count})$ $1.1M\Omega^{\sim}50M\Omega : \pm (5\% \text{ of reading} + 1 \text{ count})$ $50.1M\Omega^{\sim}2G\Omega : \pm (10\% \text{ of reading} + 1 \text{ count})$ $0.1M\Omega^{\sim}1M\Omega : \pm (5\% \text{ of reading} + 3 \text{ count})$ $1.1M\Omega^{\sim}500M\Omega : \pm (5\% \text{ of reading} + 1 \text{ count})$ $500.1M\Omega^{\sim}9.999G\Omega : \pm (10\% \text{ of reading} + 1 \text{ count})$ $10G\Omega^{\sim}50G\Omega : \pm (20\% \text{ of reading} + 1 \text{ count})^*$ $\pm (1\% + 5\text{V}) \text{ [maximum rated load} \rightarrow \text{ no load}]$		
Resistance Measurement Test Voltage 50V ≤ V ≤ 450V  500V ≤ V ≤ 1200V  Voltage Regulation Voltmeter Accuracy	Measurement Range / Accuracy $0.1M\Omega^{\sim}1M\Omega$ : ±(5% of reading + 3 count) $1.1M\Omega^{\sim}50M\Omega$ : ±(5% of reading + 1 count) $50.1M\Omega^{\sim}2G\Omega$ : ±(10% of reading + 1 count) $0.1M\Omega^{\sim}1M\Omega$ : ±(5% of reading + 3 count) $1.1M\Omega^{\sim}500M\Omega$ : ±(5% of reading + 1 count) $500.1M\Omega^{\sim}9.999G\Omega$ : ±(10% of reading + 1 count) $10G\Omega^{\sim}50G\Omega$ : ±(20% of reading + 1 count)*  ± (1% + 5V) [maximum rated load → no load]  ± (1% of reading + 5V)		
Resistance Measurement Test Voltage  50V ≤ V ≤ 450V  500V ≤ V ≤ 1200V  Voltage Regulation Voltmeter Accuracy Short-Circuit Current	Measurement Range / Accuracy $0.1M\Omega^{\sim}1M\Omega:\pm(5\% \text{ of reading}+3 \text{ count})$ $1.1M\Omega^{\sim}50M\Omega:\pm(5\% \text{ of reading}+1 \text{ count})$ $50.1M\Omega^{\sim}2G\Omega:\pm(10\% \text{ of reading}+1 \text{ count})$ $0.1M\Omega^{\sim}1M\Omega:\pm(5\% \text{ of reading}+3 \text{ count})$ $1.1M\Omega^{\sim}500M\Omega:\pm(5\% \text{ of reading}+1 \text{ count})$ $500.1M\Omega^{\sim}9.999G\Omega:\pm(10\% \text{ of reading}+1 \text{ count})$ $10G\Omega^{\sim}50G\Omega:\pm(20\% \text{ of reading}+1 \text{ count})^*$ $\pm(1\%+5\text{V}) \text{ [maximum rated load} \rightarrow \text{ no load]}$ $\pm(1\% \text{ of reading}+5\text{V})$ $10\text{mA max}.$		
Resistance Measurement Test Voltage  50V ≤ V ≤ 450V  500V ≤ V ≤ 1200V  Voltage Regulation Voltmeter Accuracy Short-Circuit Current Output Impedance	Measurement Range / Accuracy $0.1M\Omega^{\sim}1M\Omega : \pm (5\% \text{ of reading} + 3 \text{ count})$ $1.1M\Omega^{\sim}50M\Omega : \pm (5\% \text{ of reading} + 1 \text{ count})$ $50.1M\Omega^{\sim}2G\Omega : \pm (10\% \text{ of reading} + 1 \text{ count})$ $0.1M\Omega^{\sim}1M\Omega : \pm (5\% \text{ of reading} + 3 \text{ count})$ $1.1M\Omega^{\sim}500M\Omega : \pm (5\% \text{ of reading} + 1 \text{ count})$ $500.1M\Omega^{\sim}9.999G\Omega : \pm (10\% \text{ of reading} + 1 \text{ count})$ $10G\Omega^{\sim}50G\Omega : \pm (20\% \text{ of reading} + 1 \text{ count})^*$ $\pm (1\% + 5\text{V}) \text{ [maximum rated load} \rightarrow \text{ no load}]$ $\pm (1\% \text{ of reading} + 5\text{V})$ $10\text{mA max.}$ $2k\Omega$		
Resistance Measurement Test Voltage  50V ≤ V ≤ 450V  500V ≤ V ≤ 1200V  Voltage Regulation Voltmeter Accuracy Short-Circuit Current Output Impedance Window Comparator Method	Measurement Range / Accuracy $0.1M\Omega^{\sim}1M\Omega : \pm (5\% \text{ of reading} + 3 \text{ count})$ $1.1M\Omega^{\sim}50M\Omega : \pm (5\% \text{ of reading} + 1 \text{ count})$ $50.1M\Omega^{\sim}2G\Omega : \pm (10\% \text{ of reading} + 1 \text{ count})$ $0.1M\Omega^{\sim}1M\Omega : \pm (5\% \text{ of reading} + 3 \text{ count})$ $1.1M\Omega^{\sim}500M\Omega : \pm (5\% \text{ of reading} + 1 \text{ count})$ $500.1M\Omega^{\sim}9.999G\Omega : \pm (10\% \text{ of reading} + 1 \text{ count})$ $10G\Omega^{\sim}50G\Omega : \pm (20\% \text{ of reading} + 1 \text{ count})^*$ $\pm (1\% + 5\text{V}) \text{ [maximum rated load} \rightarrow \text{ no load}]$ $\pm (1\% \text{ of reading} + 5\text{V})$ $10\text{mA max}.$ $2k\Omega$ Yes		
Resistance Measurement Test Voltage 50V ≤ V ≤ 450V  500V ≤ V ≤ 1200V  Voltage Regulation Voltmeter Accuracy Short-Circuit Current Output Impedance Window Comparator Method RAMP UP (Rise Time)	Measurement Range / Accuracy $0.1M\Omega^{\sim}1M\Omega : \pm (5\% \text{ of reading} + 3 \text{ count})$ $1.1M\Omega^{\sim}50M\Omega : \pm (5\% \text{ of reading} + 1 \text{ count})$ $50.1M\Omega^{\sim}2G\Omega : \pm (10\% \text{ of reading} + 1 \text{ count})$ $0.1M\Omega^{\sim}1M\Omega : \pm (5\% \text{ of reading} + 3 \text{ count})$ $1.1M\Omega^{\sim}500M\Omega : \pm (5\% \text{ of reading} + 1 \text{ count})$ $500.1M\Omega^{\sim}9.999G\Omega : \pm (10\% \text{ of reading} + 1 \text{ count})$ $10G\Omega^{\sim}50G\Omega : \pm (20\% \text{ of reading} + 1 \text{ count})^*$ $\pm (1\% + 5\text{V}) \text{ [maximum rated load} \rightarrow \text{ no load]}$ $\pm (1\% \text{ of reading} + 5\text{V})$ $10\text{mA max}.$ $2k\Omega$ $\text{Yes}$ $0.1\text{s}^{\sim}999.9\text{s}$		
Resistance Measurement Test Voltage  50V ≤ V ≤ 450V  500V ≤ V ≤ 1200V  Voltage Regulation Voltmeter Accuracy Short-Circuit Current Output Impedance Window Comparator Method RAMP UP (Rise Time) RAMP DOWN (Fall Time)	Measurement Range / Accuracy $0.1M\Omega^{\sim}1M\Omega : \pm (5\% \text{ of reading} + 3 \text{ count})$ $1.1M\Omega^{\sim}50M\Omega : \pm (5\% \text{ of reading} + 1 \text{ count})$ $50.1M\Omega^{\sim}2G\Omega : \pm (10\% \text{ of reading} + 1 \text{ count})$ $0.1M\Omega^{\sim}1M\Omega : \pm (5\% \text{ of reading} + 3 \text{ count})$ $1.1M\Omega^{\sim}500M\Omega : \pm (5\% \text{ of reading} + 1 \text{ count})$ $500.1M\Omega^{\sim}9.999G\Omega : \pm (10\% \text{ of reading} + 1 \text{ count})$ $10G\Omega^{\sim}50G\Omega : \pm (20\% \text{ of reading} + 1 \text{ count})^*$ $\pm (1\% + 5\text{V}) \text{ [maximum rated load} \rightarrow \text{ no load}]$ $\pm (1\% \text{ of reading} + 5\text{V})$ $10\text{mA max}.$ $2k\Omega$ $\text{Yes}$ $0.1s^{\sim}999.9s$ $0.0s^{\sim}999.9s$		
Resistance Measurement Test Voltage 50V ≤ V ≤ 450V  500V ≤ V ≤ 1200V  Voltage Regulation Voltmeter Accuracy Short-Circuit Current Output Impedance Window Comparator Method RAMP UP (Rise Time)	Measurement Range / Accuracy $0.1M\Omega^{\sim}1M\Omega : \pm (5\% \text{ of reading} + 3 \text{ count})$ $1.1M\Omega^{\sim}50M\Omega : \pm (5\% \text{ of reading} + 1 \text{ count})$ $50.1M\Omega^{\sim}2G\Omega : \pm (10\% \text{ of reading} + 1 \text{ count})$ $0.1M\Omega^{\sim}1M\Omega : \pm (5\% \text{ of reading} + 3 \text{ count})$ $1.1M\Omega^{\sim}500M\Omega : \pm (5\% \text{ of reading} + 1 \text{ count})$ $500.1M\Omega^{\sim}9.999G\Omega : \pm (10\% \text{ of reading} + 1 \text{ count})$ $10G\Omega^{\sim}50G\Omega : \pm (20\% \text{ of reading} + 1 \text{ count})^*$ $\pm (1\% + 5\text{V}) \text{ [maximum rated load} \rightarrow \text{ no load]}$ $\pm (1\% \text{ of reading} + 5\text{V})$ $10\text{mA max}.$ $2k\Omega$ $\text{Yes}$ $0.1\text{s}^{\sim}999.9\text{s}$		



N0. 7-1, Jhongsing Road, Tucheng Dist., New Taipei City, 236, Taiwan

T (886) 2 2268-0389 F (886)2 2268-0639 www.gwinstek.com

WAIT TIME	0.0s~999.9s		
GND	ON/OFF		
Ground Bond	014, 011		
Output-Current	03.00A~32.00A ac		
Output-Current Resolution	0.01A		
Output-Current Accuracy	$3A \le 1 \le 8A : \pm (1\% \text{ of reading} + 0.2A)$		
,			
	8A <i≦32a +="" 0.05a)<="" :="" of="" reading="" td="" ±(1%=""></i≦32a>		
Test-Voltage	8Vac max (open circuit)		
Test-Voltage Frequency	50Hz/60Hz selectable		
Ohmmeter Measurement Range	1m $\Omega$ ~ 650m $\Omega$		
Ohmmeter Measurement Resolution	0.1m $\Omega$		
Ohmmeter Measurement Accuracy	$\pm$ (1% of reading + 2 m $\Omega$ )		
Window Comparator Method	Yes		
TIMER (Test Time)	0.3s~999.9s		
TIMER Accuracy	±(100ppm + 20ms)		
Test Method	Four Terminal		
GND	ON/OFF		
Continuity Test			
Output-Current	100mA dc (fixed)		
Ohmmeter Measurement Range	0.10Ω~ 70.00Ω		
Ohmmeter Measurement Resolution	$0.01\Omega$		
Ohmmeter Measurement Accuracy	$\pm (10\% \text{ of reading} + 2 \Omega)$		
Window Comparator Method	Yes		
TIMER (Test Time)	0.3s~999.9s		
TIMER Accuracy	±(100ppm + 20ms)		
MEMORY			
Single Step Memory	MANU: 100 blocks		
Automatic Testing Memory	AUTO: 100 blocks, manu per auto: 10		
INTERFACE			
REMOTE (Front) terminal	Standard		
USB host (Front)	Standard		
Rear Output	Standard		
RS-232C	Standard		
USB device	Standard		
Signal I/O	Standard		
GPIB	Option		
LAN	Option		
DISPLAY			
	7" color LCD		
POWER SOURCE			
	AC 100V~240V ± 10%, 50Hz/60Hz		
_	Power consumption : 400VA max.		
DIMENSION & WEIGHT			
GPT-12001/12002/12003	380(W) x 148(H) x 436(D) mm; Approx. 11kg		
GPT-12004	380(W) x 148(H) x 454(D) mm; Approx. 15kg		

<sup>#</sup> When Ground Mode is "ON", the measurement range is 30GΩ max. and adding 10% error for accuracy.